



## ITU G.729A/G.729A+B Speech Coder

**SIGNALS+SOFTWARE**



### Processor

Motorola StarCore™ MSC8101 DSP.

### Background

**SIGNALS+SOFTWARE** are developing a complete suite of communication software for the Motorola MSC8100 family of DSPs. The initial development platform, the MSC8101, utilizes the StarCore™ 140 four ALU (Algorithmic Logic Unit) DSP core. This device also has 512kb memory and a Communications Processor Module (CPM) making it a versatile device for communication applications.

The algorithms implemented are the ITU-T recommendations G.729 Annex A and G.729 Annex A + Annex B fixed rate speech coders for internet and multimedia communications. G.729A is a reduced complexity version of G.729 with similar audio performance in most circumstances

G.729A+B comprises of G.729A with the additional option of Annex B. Annex B uses silence compression or discontinuous transmission to reduce the transmitted bit rate during the silent intervals of speech. Voice Activity Detection (VAD) and Comfort Noise Generation (CNG) algorithms are used to enable the transmission of Silence Descriptor (SID) frames during the periods of silence. This provides the additional advantage of using lower processing loads and DSP bandwidth resource during silence intervals.

### Features and Performance

- Passes all ITU-T test vectors
- Please see Table 3 containing predicted figures for G.729A+B following further optimisation.

G.729A	Program Memory (Kbytes)	Tables (Kbytes)	Stack Memory (Kbytes)	Static Memory (Kbytes)	Processing Load (MHz)
Encoder	58.3	1.3	4.9	n * 1.8	n * 7.1
Decoder	27.9	0.3	4.9	n * 2.0	n * 2.1
Encoder + Decoder	72.3	4.4	4.9	n * 3.8	n * 9.1

**Table 1 : Current DSP Requirements for G.729A**

G.729A+B	Program Memory (Kbytes)	Tables (Kbytes)	Stack Memory (Kbytes)	Static Memory (Kbytes)	Processing Load (MHz)
Encoder	58.3	1.5	4.9	n * 2.1	n * 7.0
Decoder	27.9	0.3	4.9	n * 2.0	n * 2.3
Encoder + Decoder	72.3	4.8	4.9	n * 4.1	n * 9.3

**Table 2 : Current DSP Requirements for G.729A+B**

**Note:** Processing loads quote worst-case scenarios using ITU-T test vectors. n represents the number of channels. Program memory table values are initialisation values. Kbytes equal 1024 bytes.

<b>G.729A+B</b>	<b>Program Memory (Kbytes)</b>	<b>Tables (Kbytes)</b>	<b>Stack Memory (Kbytes)</b>	<b>Static Memory (Kbytes)</b>	<b>Processing Load (MHz)</b>
Encoder + Decoder	75K	4.8K	5K	n * 4.1	n * 6

**Table 3 : Predicted DSP Requirements for G.729A+B**

**Note:** Processing loads quote worst-case scenarios using ITU-T test vectors. n represents the number of channels. Program memory table values are initialisation values. Kbytes equal 1024 bytes.

**Technical Notes**

The ITU-T G.729A recommendation compresses narrowband speech and audio signals at a sample rate of 8kHz to 8 000 bps, using a linear predictive analysis-by-synthesis coding, Conjugate-Structure Algebraic-Code-Excited Linear Prediction (CS-ACELP). The coder operates on 10ms frames to extract the parameters of the CELP coding model. The decoder uses two filters. One is based on a 10th order Linear Prediction (LP) filter, the other is based on an adaptive-codebook approach. Additional performance enhancement is achieved by use of a Post Filter.

**Interface Details**

For convenience the individual software functions are supplied as a single library module. The library contains all the object code that is required to link in to a user's top - level application code. The audio functions are either callable as C functions or as assembly functions.

**Availability**

Code for G.729A and G.729A+B is available now, for a one-off payment and/or royalties depending on the commercial application.

Also available for StarCore™ are a full range of vocoders including G.711, G.722, G.723.1, G.726, G.728, G.729, G.729+B and other communication algorithms.

**SIGNALS+SOFTWARE**

**SIGNALS+SOFTWARE** was founded in 1992 as a developer of high quality Digital Signal Processing application software for the communications industry. Supplying to a whole range of customers, including large blue chip corporations, **SIGNALS+SOFTWARE** has quickly established itself as the world leader in DSP software design and production.

**For further information please contact:**

**SIGNALS+SOFTWARE Ltd.**  
 The Heights,  
 Lowlands Road,  
 Harrow,  
 HA1 3AW  
 United Kingdom

**Tel: +44 (0) 20 8872 9000**  
**Fax: +44 (0) 20 8872 9001**  
[www.signalsandsoftware.com](http://www.signalsandsoftware.com)  
[sales@signalsandsoftware.com](mailto:sales@signalsandsoftware.com)

© Signals+Software, 2002. All trademarks are recognized. This document contains information on products under development. Signals+Software reserves the right to change or discontinue these products without notice. S+S makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does S+S assume any liability arising out of the application or use of any product, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. This document supercedes earlier documentation relating to the products referred to herein. The information contained in this document is current at the date of publication. It may subsequently be updated, revised or withdrawn.