



ITU G.729/G.729B Speech Coder

SIGNALS+SOFTWARE



Processor

Motorola DSP56300 range.

Background

The algorithms implemented are the ITU-T G.729 and G.729+B recommendations, fixed rate speech coders for internet and multimedia communications. G.729 compresses narrowband speech and audio signals at a sample rate of 8kHz to 8 000 bps, using a linear predictive analysis-by-synthesis coding, Conjugate-Structure Algebraic-Code-Excited Linear Prediction (CS-ACELP). The coder operates on 10ms frames to extract the parameters of the CELP coding model. The decoder uses two filters. One is based on a 10th order Linear Prediction (LP) filter, the other is based on an adaptive-codebook approach. Additional performance enhancement is achieved by use of a Post Filter.

G.729+B includes G.729 with the additional option of Annex B. Annex B implements silence compression techniques to reduce the transmitted bit rate during the silent intervals of speech and conforms to Recommendation V.70 silence compression. Systems allowing discontinuous transmission (DTX) are based on Voice Activity Detection (VAD) algorithms and Comfort Noise Generator (CNG) algorithms that allows the insertion of Silence Insertion Descriptor (SID) frames during the silence intervals. This also provides the additional advantage of using lower processing loads and DSP bandwidth resource during silence frames.

Features and Performance

- Approximately 4channels of G.729 on 100MHz device
- Approximately 4 channels of G.729+B on 100MHz device
- Less than 16K words of program memory required for either G.729 or G.729+B
- Less than 13kwords of data memory required for 4 channels of G.729
- Less than 14kwords of data memory required for 4 channels of G.729+B (including buffers and stack)
- Passes all ITU-T test vectors

G.729	Program Memory		X Data Memory		Y Data Memory		Processing Load (MHz)
	Code (Kwords)	Tables (Kwords)	Variables (Kwords)	Tables (Kwords)	Variables (Kwords)	Tables (Kwords)	
Encoder	6.05	2.92	1.67+n*0.23	1.51	1.48+n*0.44	1.41	n*20.79
Decoder	3.04	2.24	1.48+n*0.06	1.4	0.4+n*0.67	0.84	n* 3.55
Encoder + Decoder	8.33	3.09	1.97+n*0.29	1.65	1.5+n*1.11	1.44	n*24.34

Table 1 : DSP Requirements for G.729

Note: Processing loads quote worst-case scenarios with n representing the number of channels. Program memory table values are initialisation values. 1 word equals 24 bits. Kwords equals 1024 words

G.729+B	Program Memory		X Data Memory		Y Data Memory		Processing Load (MHz)
	Code (Kwords)	Tables (Kwords)	Variables (Kwords)	Tables (Kwords)	Variables (Kwords)	Tables (Kwords)	
Encoder	9.05	3.21	1.74+n*0.3	1.51	1.54+n*0.52	1.7	n*21.06
Decoder	4.07	2.45	1.5+n*0.06	1.41	0.4+n*0.69	1.04	n* 3.58
Encoder + Decoder	11.76	3.38	2.05+n*0.36	1.65	1.56+n*1.21	1.73	n* 24.64

Table 2 : DSP Requirements for G.729+B

Note: Processing loads quote worst-case scenarios with n representing the number of channels.
 Program memory table values are initialisation values. 1 word equals 24 bits. Kwords equals 1024 words

Interface Details

For convenience the individual software functions are supplied as a single library module. The library contains all the object code that is required to link in to a user's top-level application code.

Availability

Fully optimised code for G.729 and G.729+B is available now, for a one-off payment and/or royalties depending on the commercial application.

Also available for DSP56300 are a full range of vocoders including G.711, G.722, G.726, G.728, G.729A, G.729A+B and other communication algorithms.

SIGNALS+SOFTWARE

SIGNALS+SOFTWARE was founded in 1992 as a developer of high quality Digital Signal Processing application software for the communications industry. Supplying to a whole range of customers, including large blue chip corporations, **SIGNALS+SOFTWARE** has quickly established itself as the world leader in DSP software design and production.

For further information please contact:

SIGNALS+SOFTWARE Ltd.
 The Heights,
 Lowlands Road,
 Harrow,
 HA1 3AW
 United Kingdom

Tel: +44 (0) 20 8872 9000
 Fax: +44 (0) 20 8872 9001

www.signalsandsoftware.com

sales@signalsandsoftware.com

© Signals+Software, 2002. All trademarks are recognized. This document contains information on products under development. Signals+Software reserves the right to change or discontinue these products without notice. S+S makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does S+S assume any liability arising out of the application or use of any product, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. This document supercedes earlier documentation relating to the products referred to herein. The information contained in this document is current at the date of publication. It may subsequently be updated, revised or withdrawn.